

Amendments to the Claims:

1. (currently amended) A method for filtering a video stream to reduce ~~reducing~~ a blocking artifact in a ~~video stream~~ post-processing de-blocking device of a video decoder, the method comprising:

5

determining a region mode for a block boundary between a plurality of adjacent blocks in the video stream; and

10

utilizing a de-blocking filtering unit for filtering a plurality of pixels around the block boundary to reduce the blocking artifact according to the region mode;

wherein filtering the pixels around the block boundary comprises first filtering the pixels at the block boundary and next filtering pixels not adjacent to the pixels at the block boundary;

15

determining the region mode for the block boundary between the adjacent blocks in the video stream further comprises:

20

calculating an activity value representing the local activity around the block boundary; and

determining the region mode according to the activity value;

25

calculating the activity value comprises summing absolute differences between pixels V_l around the block boundary as follows:

$$ACTIVITY = \sum_{l=4}^6 |v_l - v_{l+1}| + \sum_{l=8}^{10} |v_l - v_{l+1}|;$$

if at least one of the adjacent blocks is an intra-coded block:

if the activity value is greater than a first threshold, determining the region mode to be an active region;
if the activity value is less than the first threshold but greater than a second threshold, determining the region mode to be a smooth region; and

if the activity value is less than the second threshold, determining the region mode to be a dormant region; and

if none of the adjacent blocks are intra-coded blocks:

if the activity value is greater than a third threshold, determining the region mode to be an active region;

if the activity value is less than the third threshold but greater than the second threshold, determining the region mode to be a smooth region; and

if the activity value is less than the second threshold, determining the region mode to be a dormant region.

20

2. (original) The method of claim 1, wherein filtering the plurality of pixels further comprises filtering pixels at the block boundary, filtering pixels away from the block boundary, and then filtering remaining pixels between the pixels at the block boundary and the pixels away from the block boundary.

25

3-5. (cancelled)

6. (previously presented) The method of claim 1, wherein the second threshold is fixed at a predetermined value.

30

7. (original) The method of claim 6, wherein the predetermined value is 6.

8. (original) The method of claim 7, further comprising:

if at least one of the adjacent blocks is an intra-coded block:

5

if the region mode is active region, if a high frequency component c_3 is less than a fourth threshold, filtering the pixels around the block boundary according to the filtering range using a first filter;

10

if the region mode is smooth region,

if the absolute value of the difference of the pixel values on either side of the block boundary is less than a fifth threshold, filtering the pixels around the block boundary according to the filtering range using a second filter; and

15

if the region mode is dormant region,

if the absolute value of the difference of the pixel values on either side of the block boundary is less than the fifth threshold, filtering the pixels around the block boundary according to the filtering range using a third filter; and

20

if none of the adjacent blocks are intra-coded blocks:

25

if the region mode is active region, if the high frequency component c_3 is less than a sixth threshold, filtering the pixels around the block boundary according to the filtering range using the first filter;

30

if the region mode is smooth region,

if the absolute value of the difference of the pixel values on either side of the block boundary is less than a seventh threshold, filtering the

pixels around the block boundary according to the filtering range
using the second filter; and

if the region mode is dormant region,

5 if the absolute value of the difference of the pixel values on either side
of the block boundary is less than the seventh threshold, filtering the
pixels around the block boundary according to the filtering range
using the third filter.

10 9. (original) The method of claim 8, further comprising adaptively determining the
first, third, fourth, fifth, sixth, and seventh thresholds by at least taking into
account differences in quantization parameters QPs of the adjacent blocks.

15 10. (original) The method of claim 9, further taking into account a user defined offset
(UDO) allowing the threshold levels to be adjusted according to the UDO value.

11. (original) The method of claim 8, wherein the high frequency component c_3 is
calculated using pixels v_6, v_7, v_8, v_9 around the block boundary as follows:
$$c_3 = (v_6 - v_7 + v_8 - v_9) / 2.$$

20

12. (original) The method of claim 8, wherein the first filter is a one dimensional
filter formed by using a 4-point Hadamard Transform (HT), wherein the high
frequency coefficient of the HT is reduced to 0 for frame-coded pictures.

25 13. (original) The method of claim 8, wherein the first filter is a one dimensional
filter formed by using a 4-point Hadamard Transform (HT), wherein the high
frequency coefficient of the HT is reduced to one half for field-coded pictures.

30 14. (original) The method of claim 8, wherein the filtered pixels are further refined
by adjusting a pixel quantized with a larger QP to have more change in value

than a pixel quantized with a smaller QP.

15. (original) The method of claim 14, wherein a first weighting value WT1 and a second weighting value WT2 are used for adjusting the filtered pixels and are obtained from a first quantization parameter QP1 of a first adjacent block and a second quantization parameter QP2 of a second adjacent block as follows:

$$WT1 = QP1 / (QP1 + QP2) \quad , \quad WT2 = QP2 / (QP1 + QP2)$$

16. (original) The method of claim 8, further comprising:

when the region mode is smooth region and the QPs of the adjacent blocks are the same, filtering the pixels around the block boundary with an N-tap symmetric second filter;

when the region mode is smooth region and the QPs of the adjacent blocks are not the same, filtering the pixels around the block boundary with an M-tap asymmetric second filter;

when the region mode is dormant region and the QPs of the adjacent blocks are the same, filtering the pixels around the block boundary with a K-tap symmetric filter third filter; and

when the region mode is dormant region and the QPs of the adjacent blocks are not the same, filtering the pixels around the block boundary with an L-tap asymmetric third filter.

17. (original) The method of claim 16, wherein:

N=5 and the symmetric second filter is [1 3 8 3 1]/16;

M=5 and the asymmetric second filter is $[1\ 2\ 8\ 3\ 2]/16$ and $[2\ 3\ 8\ 2\ 1]/16$;

K=5 and the symmetric third filter is $[1\ 2\ 2\ 2\ 1]/8$; and

5

L=5 and the asymmetric third filter is $[1\ 1\ 2\ 2\ 2]/8$ and $[2\ 2\ 2\ 1\ 1]/8$.

18. (original) The method of claim 1, further comprising if the video stream
comprises interlaced video, performing an interpolation operation to estimate
10 pixel values in an interlaced field before filtering the pixels around the block
boundary.

19. (original) The method of claim 1, further comprising determining a filtering
range according to block coding types of the adjacent blocks in the video stream;
15 wherein the filtering range specifies a number of pixels to filter around the block
boundary.

20. (original) The method of claim 19, wherein according to the block coding types
of the adjacent blocks in the video stream, the filtering range is determined to be
20 up to eight pixels around the block boundary.

21. (original) The method of claim 19, wherein determining the filtering range
according to the block coding types of the adjacent blocks in the video stream
further comprises:

25

if at least one of the adjacent blocks is an intra-coded block, determining the
filtering range to be up to four pixels around the block boundary; and

if none of the adjacent blocks are intra-coded blocks, determining the filtering
30 range to be up to eight pixels around the block boundary.

22. (original) The method of claim 1, wherein the video stream is an MPEG video stream.

5 23. (previously presented) The method of claim 1, wherein when filtering the pixels not adjacent to the pixels at the block boundary, there is at least one pixel left unfiltered between the pixels around the block boundary and the pixels not adjacent to the pixels at the block boundary

10 24. (currently amended) A method for filtering a video stream to reduce ~~reducing~~ a blocking artifact in a ~~video stream~~ post-processing de-blocking device of a video decoder, the method comprising:

15 determining a region mode for a block boundary between a plurality of adjacent blocks in the video stream; and

utilizing a de-blocking filtering unit for filtering a plurality of pixels around the block boundary to reduce the blocking artifact according to the region mode;

20 wherein filtering the pixels around the block boundary comprises first filtering the pixels at the block boundary and next filtering pixels not adjacent to the pixels at the block boundary;

25 determining the region mode for the block boundary between the adjacent blocks in the video stream further comprises:

calculating an activity value representing the local activity around the block boundary; and

30 determining the region mode according to the activity value; and

if at least one of the adjacent blocks is an intra-coded block:

- 5 if the activity value is greater than a first threshold, determining the region mode to be an active region;
 if the activity value is less than the first threshold but greater than a second threshold, determining the region mode to be a smooth region; and

10 if the activity value is less than the second threshold, determining the region mode to be a dormant region; and

if none of the adjacent blocks are intra-coded blocks:

- 15 if the activity value is greater than a third threshold, determining the region mode to be an active region;

 if the activity value is less than the third threshold but greater than the second threshold, determining the region mode to be a smooth region; and

20 if the activity value is less than the second threshold, determining the region mode to be a dormant region.